WINE ENTHUSIAST.

EUROCAVE® PERFORMANCE 59

BUILT-IN WINE CELLAR



BENEFITS

- Will provide years of smooth, quiet, vibration-free service with the utmost ease of operation
- Stored in these true wine cellars, your finest vintages will develop to their full potential
- Built-in versatility: build this wine cellar into your kitchen counter, or stand it on the floor in your den, TV room, or office
- Security lock and key will keep your valuable collection protected

FEATURES	
SHELVING	Rolling
INTERIOR LIGHTING	Amber Tone LED
CONTROLS	Digital
TEMPERATURE DISPLAY	Amber LED
GLASS DOOR	UV Tinted, Dual Pane
REVERSIBLE DOOR	Yes
SECURITY LOCK	Yes
WARRANTY	1-Year Parts & Labor 5 Years Sealed System
CHARCOAL FILTER	Yes
LEVELING LEGS	2

GENERAL INFORMATION		
BOTTLE CAPACITY*	Maximum 38 Bottles	
USABLE VOLUME	3.9 Cu. Ft.	
INSTALLATION TYPE	Free Standing / Built-In	
VENTING	Front	
TEMPERATURE ZONES	1 Temp	
TEMPERATURE RANGE	41°F – 68°F	
DOOR STYLES	Full Glass Door	
HANDLE	Full Glass Handle	
STORAGE RACKS – QUANTITY	4	
STORAGE RACKS – TYPE	4 Rolling MDS	
STORAGE RACKS – FRONT TRIM	Beechwood	
SHELF EXTENSION	74%	
SUGGESTED AMBIENT TEMPERATURE (F)	32°F – 86°F	

^{*}Maximum bottle capacity may vary depending on bottle size and shelf configuration.

DOOR TRIM	TEMPERATURE ZONE	HINGE	SHELF TRIM	MODEL
Full Glass Door	Single Zone	Right Hinge	Beechwood Trim Shelves	258 05 01 3X
Full Glass Door	Single Zone	Left Hinge	Beechwood Trim Shelves	258 05 01 4X

PERFORMANCE 59

BUILT-IN WINE CELLAR



DIMENSIONS & WEIGHT		
WINE CELLAR DIMENSIONS	32¾"H x 23½"W x 21¾"D*	
MINIMUM DIMENSIONS OF BUILT-IN AREA	33"H x 23¾"W x 22½"D	
GROSS SHIPPING WEIGHT	Approximately 140 lbs.	
NET WEIGHT	Approximately 126 lbs.	

^{*}Handle adds 2" to depth.

ELECTRICAL	
ELECTRICAL REQUIREMENTS	115V / 60HZ
RATED POWER INPUT	345 Watts
RATED CURRENT	3 Amps
REFRIGERANT	R600A
ENERGY CONSUMPTION	172 kwh/year
PLUG TYPE	Right Angle NEMA 5-15P Plug with SJT 3X18AWG Cord
BREAKER SIZE	15 Amp Line
DECIBEL RATING	41 dB(A)

Multiple Unit Note: If there is more than one cellar on a line, a 20 Amp circuit is required

EUROCAVE PERFORMANCE 59 BUILT-IN WINE CELLAR • WINE CABINET INSTALLATION DIAGRAM

INSTALLATION AS A BUILT-IN CELLAR

These cut out dimensions show the minimum space required for your wine cellar to perform as designed.

